

Avtron XPH1 SMARTSafeTM Encoder



Severe Duty Encoder for TDS9/10/11 Mounting with Flameproof and Explosion Proof Ratings

Magnetic Durability in a Compact Encoder

Fits NOV TDS 9, 10 & 11 Top Drives Directly

No Barrier or Isolator Needed

No Intrinsic Safety Ground Required

Class I Div 1 Groups C, D Listed

AEx Zone 1 Certified

Fully Protected Against Shorts and Wiring Errors

Drives up to 1000 feet [305m] of cable without repeaters

2 Year No-Hassle Warranty

-50°C to +85°C Operation

Zone 1 & 2 Certified

XPH₁

Dramatically slash encoder-related downtime on top drive applications!

XPH1 SMARTSafe[™] encoders are the world's first explosion-proof encoders with removable electronics and no external barrier! They are cULus, ATEX, IECEx certified and offer incredibly reliable no-bearing construction! SMARTSafe XPH1 encoders can be used in ATEX/IECEx, cUL AEX, and UL gas hazardous environments including NEC500 and NEC 505.

XPH1 comes complete with auto-centering jig, base plate, riser shaft, sensor and rotor to fit NOV TDS9, TDS10, and TDS11. Also available: nobearing modular sensors (XP5), 8.5" C-face XPH8 as well as intrinsically safe models (XR5, XR12, XR56A, XR125, XR485, XR685, XR850) and hollow shaft models M6C.

Use the XPH1 directly in your application with no barrier or isolator required with 1000 feet of cable or more!


Unlike the competition, Avtron SMARTSafe encoder systems are protected against short circuits, power-to-output wiring, and output-to-ground faults. They feature full diagnostics: it's easy to determine that signal quality is good-just look for the green LED. Worried about wiring short circuits and errors? XPH1 will indicate any short circuit conditions with an orange LED and will survive this condition!


No encoder bearing failures, no more sealing problems. Mount XPH1 directly on your motor, build it right into your machine. So many applications benefit from a more reliable no-bearing encoder. Vibration, shock, liquids, dust and dirt won't harm SMARTSafe XPH1 encoders!

Eliminate the biggest cause of hazardous duty encoder failure--eliminate the bearings with XPH1 hazardous duty encoders!



OUTLINE DRAWING





MORE XPH1 ADVANTAGES

- All-digital design, no trim pots or adjustments for longer life
- · Advanced sensor technology
- Superior line drivers withstand short circuits and reverse voltage wiring errors
- Fully Potted Electronics
- SMARTSafe sensors find problems before they cause failure
- Allows Gland or Conduit Connections
- Full protection against motor shaft currents

MORE XPH1 SPECIFICATIONS

Operating Power: 5-24VDC in/out 400mA max @ 5V; 200mA max @ 12V; 100mA max @ 24V (plus cable load) Output Format: A Quad B with marker (A, /A, B, /B, Z, /Z)

Frequency Range: 0 to 250 kHz PPR: 8-100000

Speed: 6000 RPM Max. (contact factory for higher speeds)

Maximum Cable Length: 1000 ft (305m) (contact factory for longer distances) Rotor Positioning: Up to +/-0.100" [+/-2.54mm] movement/misalignment Sensor-Rotor Gap: 0.040", +0.015/-0.030" [1mm+0.38/-0.76]

Temperature: -50°C to 85°C

(rotor -50°C to 100°C continuous, +135°C intermittent)

Environmental: IP65 fully potted sensors Vibration: 5-2000Hz, 18G; 100G Shock

Weight: 15lbs. [6.8kg]

Certifications:

Class I Div 1, Groups C and D Class I Zone 1, Ex db ia IIB T4 Gb Class I Zone 1, AEx db ia IIB T4 Gb Ex db ia IIB T4 Gb (ATEX/IECEx)

*See installation drawings for Warnings and Limitation **Consult NOV for installation guidelines and details

Check out our website for more detailed specifications, drawings, and installation instructions. www.avtronencoders.com



Nidec Industrial Solutions

SELECTION GUIDE

MODEL	ROTOR STYLE	COVER STYLE	ОИТРИТ	LEFT OUTPUT PPR	RIGHT OUTPUT PPR	CONNECTION OPTIONS	MODIFICATIONS
XPH1	XX - No Rotor A1 - Rotor to fit TDS 9/10/11	X - No Cover	8 - 5-24vDC in/out Hi- Powered, Protected, HX Line Driver	XX - None BC - 50 PPR AF - 60 PPR AK - 80 PPR AK - 80 PPR AK - 80 PPR AM - 200 PPR AP - 300 PPR AP - 300 PPR AP - 300 PPR AC - 400 PPR AC - 400 PPR AM - 500 PPR AM - 500 PPR AM - 500 PPR AM - 500 PPR AM - 900 PPR AM - 900 PPR AM - 1000 PPR AM - 1000 PPR AM - 1000 PPR AM - 1000 PPR AM - 500 PPR AM - 4004 PPR AM - 5000 PPR	XX - None	A - w/screw-type terminal block, M25 Thread on both exits, Blanking Plug installed on right side, A Leads B with CW Rotation B - w/screw-type terminal block, M25 Thread on both exits, Blanking Plug installed on left side, A Leads B with CW Rotation	000 - No Special Options

